

USB Digital Input/Output Device

3xLOGIC's VH-UDIO-1204 allows VIGIL Server users to monitor and control many facets of the environment that their VIGIL Server protects. With direct integration into VIGIL Server, the VH-UDIO-1204 offers the ability to monitor 12 inputs and trigger 4 outputs through a USB powered connection.

With the VH-UDIO-1204's 12 inputs, you can monitor and know the status of:

- Contact closures
- Door contacts
- Safe openings
- Cash register openings
- Panic alarms
- Call buttons/intercoms
- Gate contacts

Additionally, with any of your 4 outputs you can:

- Trigger a relay
- Trigger an output, like opening a door or gate or initiating a siren or flashing light
- Start recording video in alarm mode
 - ▶ Change the FPS
 - ▶ Creates colored flags within the Enhanced Visual Search for easy identification
- Start recording audio



ELECTRICAL

| | |
|---------------------------|---------------------------------------|
| Power Supply: | DC5V, 500mA, Powered by USB Interface |
| Power Consumption: | ≤1W (with Load ≤2.5W) |

INTERFACE

| | |
|-----------------------|--|
| Communication: | 1 USB 2.0 Interface (4-pin) |
| Alarm Input: | 12 channel signal input |
| Alarm Output: | 4 channel signal relay output 200mA Max Current |

PHYSICAL

| | |
|-----------------------------|-----------------------------|
| Working Temperature: | -10°C ~ 55°C (14°F - 131°F) |
| Working Humidity: | 10% ~ 90% |
| Dimensions (inches): | 4.96" x 4.41" x 1.14" |
| Dimensions (mm): | 126 x 112 x 29 |
| Weight: | .90 lbs. / .40 kg |

WARRANTY

Three (3) Year Return to Depot Parts and Labor Warranty

PART NUMBER

| | |
|----------------------|----------------------------|
| VH-UDIO-1204: | USB Digital Input & Output |
|----------------------|----------------------------|